CSA121A PASSIVE WIDEBAND COMBINER → 1 x 2:1
PASSIVE WIDEBAND SPLITTER → 1 x 1:2

CSA121A is designed to combine different areas, covered by antennas in diversity configuration. CSA121A is DC-coupled for use with antenna booster: it can handle up to 1.5 Amp without saturation for high power booster (BAW) powering. Mounting plate hole M5.
It is supplied with a power supply for the booster voltage.
In case a booster voltage is not needed, use the CSA221 to have a double splitter combiner.

FEATURES:

- ✓ Small and compact splitter/combiner, stripline construction
- ✓ Wide band operation
- ✓ High current standing for high IP3 booster driving (i.e. Wisycom BAW)
- ✓ Supplied with 230/110 Vac power supply with locking connector



Instruction

Combining:	Input are [1] & [2]	→	output [C] (combined signals)
Splitter:	Input is [C]	→	output [1] & [2] (split signals)

Variant

STD	standard version	combiner and splitter
SPL	splitter version	only splitter
COM	combiner version	only combiner

Technical Data

Connectors: 3 Bnc-F
Splitter/Combiner loss: 4 dB
Max current thru port: 1.5 A
Max input power (CSA121A) : 125 mW
Bandwidth: 470 MHz – 870MHz
Case: Aluminum, black varnish
Weight: 220 g
Impedance: 50 Ω

COMBINER CONFIGURATION WITH HIGH CURRENT BOOSTER



COMBINER CONFIGURATION WITH HIGH POWER TRANSMITTER



Wisycom Srl - Via Spin, 156 - I-36060 Romano d'Ezzelino (VI) - Italy
tel. +39 0424 382605 fax. +39 0424 382733 http:// www.wisycom.com - e-mail: sales@wisycom.com
Iscrizione al Registro A.E.E. n. IT09100000006319

Subject to change without notice